

OWNER'S MANUAL —

Before using the product, please read the instructions thoroughly and retain them for future reference.

8065308

IMPORTANT SAFETY INSTRUCTIONS

When using your telephone equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injuries to individuals, including the following:

1. Do not use this product near water, for example, near a bath tub, wash bowl, kitchen sink or laundry tub, in a wet basement or near a swimming pool.
2. Avoid using a telephone (other than a cordless type) during an electrical storm. There may be a remote risk of electrical shock from lightning.
3. Do not use the telephone to report a gas leak in the vicinity of the leak.

INTRODUCTION

The Nextech™ Easy Dial Phone connects directly to a modular telephone line jack. It can be placed on a desk or mounted directly to a wall or wall plate (not included).

WHAT'S INCLUDED

- Easy Dial Phone
- Long modular cord
- Short modular cord
- Owner's manual



EASY DIAL PHONE

1. **STORE/MUTE**
Press to mute the call or store a telephone number
2. **MEMORY**
Press to store a phone number or to dial the stored number
3. **FLASH**
Press for call waiting (if you do not have call waiting pressing FLASH may disconnect the call)
4. **REDIAL**
Press to dial the last number dialed
5. **VOL**
Repeatedly press ▲ or ▼ to increase or decrease the volume
6. **3 Emergency numbers**
7. **Tone/Pulse**
Slide to switch between tone (T) and pulse (P) dialing

HEARING AID COMPATIBLE

- This phone is hearing aid compatible

MOUNTING THE PHONE ON A DESKTOP

1. Plug one end of the supplied modular cord into the jack on the bottom of the base.
2. Route the cord through the groove on the base's bottom.
3. Plug the other end into a modular phone jack.

MOUNTING THE PHONE ON A WALL

1. Drill 2 holes 100mm (3 15/16") apart, one below the other.
2. Thread 2 screws (not included) through the holes allowing about 3/16" of the screw heads to extend from the wall. Please ensure that the heads of the screws fit into the keyhole slots on the bottom of the phone.
3. Fit the heads of the screws into the keyhole slots, then slide the base down until it is secure.
4. Plug the other end of the cord into a modular phone jack.

STORING TELEPHONE NUMBERS

You can store up to 13 numbers in memory—3 emergency numbers and 10 standard memory numbers.

STORING AN EMERGENCY NUMBER

1. Pick up the handset.
2. Press STORE/MUTE. The LED will flash.
3. Press the corresponding icon (police, fire or ambulance)
4. Enter the telephone number you wish to store.
5. Press STORE/MUTE to confirm. The LED will stop flashing.
6. To delete a stored number, simply store a new number in it's place.

STORING A TELEPHONE NUMBER

1. Pick up the handset.
 2. Press STORE/MUTE. The LED will flash.
 3. Press MEMORY and the desired number button.
 4. Enter the telephone number you wish to store.
 5. Press STORE/MUTE to confirm. The LED will stop flashing.
 6. To delete a stored number, simply store a new number in its place.
- To keep a record of stored numbers use a flat screwdriver to lift the plastic cover from the under card under the handset. Use a pencil in case you need to change any of the numbers at a later date.

SELECTING THE RING TONE

There are 3 different ring tones and volume levels for your telephone.

1. Pick up the handset.
 2. Press STORE/MUTE. Then press #.
 3. Press a number button (0-9) to set the ring tone and ring volume.
 4. Press STORE/MUTE again.
 5. Hang up the handset.
- NOTE: If 0 is selected the ringer type will be turned off until the next time you pick up the receiver. It will then revert back to the previously selected ring tone.

DIGIT	RING TONE	VOLUME
1	Music	Low
2	Music	Medium
3	Music	High
4	Standard	Low
5	Standard	Medium
6	Standard	High
7	Quick	Low
8	Quick	Medium
9	Quick	High
0	OFF	OFF

DIALING A STORED NUMBER

1. Pick up the handset.
2. To dial an emergency number press the required emergency icon.
Note: Please follow above procedure to program the emergency numbers into the emergency buttons.
3. To dial a number stored in memory press MEMORY and the location number

CARE AND MAINTENANCE

- Keep your phone dry
- Handle with care. DO NOT drop
- **DO NOT** use or store in extreme temperatures
- **DO NOT** modify or tamper with the phone's internal components. Doing so may cause the phone to malfunction and will void the warranty

NOTE: This telephone requires a modular telephone line jack. If you do not have one you will need to update your wiring, or have your local telephone company update it for you. You must use compatible modular jacks that are compliant with part 68 of FCC rules.

- The USOC number of the jack must be RJ11C (RJ11W for a wall plate jack)

SETUP

Your telephone connects directly to a modular telephone line jack. If your telephone wiring does not have a modular jack, you can update the wiring yourself using jacks and adapters, or have the telephone company update the wiring for you.

Note: The CSA number of the jack to be installed is CA11C (or CA11W for a wall plate jack).

If your home has specially wired alarm equipment connected to the telephone line, be sure that installing the telephone does not disable your alarm equipment. If you have questions about what will disable your alarm equipment, contact your telephone company or a qualified installer.

SERVICE AND REPAIR

Modifying or tampering with the telephone's internal components can cause a malfunction and might invalidate its warranty.

INDUSTRY CANADA CS03 STATEMENT

This product meets the applicable Industry Canada technical specifications. This is confirmed by the registration number. The abbreviation, IC before the registration number signifies that registration was performed based on a Declaration of Conformity indicating that Industry Canada technical specifications were met. It does not imply that Industry Canada approved the equipment. Before installing this equipment, users should ensure that it is permissible to be connected to the facilities of the local telecommunications company.

The equipment must also be installed using an acceptable method of connections. The customer should be aware that compliance with the above conditions may not prevent degradation of service in some situations. Repairs to certified equipment should be made by an authorized Canadian maintenance facility designated by the supplier. Any repairs or alterations made by the user of this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

WARNING! Users should not attempt to make such connections themselves, but should contact the appropriate electric inspection authority, or an electrician, whichever is appropriate.

CAUTION: The Ringer Equivalence Number (REN) assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5. An alternative indication of the REN is the Load Number (LN); this number should be divided by 20 to approximate the equivalent REN. The REN Number of this unit is indicated on the bottom.

CAN ICES-3(B).

THE SOURCE - WARRANTY

The Source warrants that this product will be free from defects in materials and workmanship for a period of one (1) year from the date of purchase. Within this period, simply take the product and your proof of purchase to any The Source store or participating dealer and the product will be replaced (where available) without charge. Any product which has been subject to misuse or accidental damage is excluded from this warranty.

This warranty is only applicable to a product purchased through The Source company-owned stores or participating dealers in Canada where the warranty is included with the product. While this warranty does not confer any legal rights other than those set out above, you may have additional statutory rights which will vary under the laws of the various countries, states, provinces and other governmental entities in which The Source operates. This warranty is subject to all statutory rights you may have in Canada.

Imported by The Source
Barrie, Ontario, Canada, L4M 4W5
Manufactured in China
www.thesource.ca

© 2017 The Source
All rights reserved.



Please Recycle