



LCD TRAVEL ALARM CLOCK



8065426

OWNER'S MANUAL


FEATURES

- Large LCD display
- 12/24 hour format
- Alarm
- Daily Snooze
- Light button
- Perpetual Calendar Up to Year 2069
- Temperature measures °C/°F
- Indoor measureable range: 0°C~+49.9°C
- Stand

FRONT VIEW



REAR VIEW



FEATURES

- | | |
|---------------------------|-------------------------|
| 1: AM/PM indicator | 9: ▲12/24 button |
| 2: Time | 10: SNOOZE/LIGHT button |
| 3: Alarm icon | 11: °C/°F button |
| 4: Date | 12: ▼button |
| 5: Day of the week | 13: RESET button |
| 6: Temperature | 14: Battery cover |
| 7: ALARM ON/OFF Slide key | |
| 8. MODE button | |

GETTING STARTED

Open the battery cover located at the back of the clock and insert 2 x AAA alkaline batteries (not included), as indicated by the polarity markings. Replace the cover. *We recommend InfiniCell batteries for maximum performance.*

TIME AND ALARM SETTING

Time Setting:

- Hold the MODE button for 3 seconds to enter Clock/Calendar setting
- Press ▲ or ▼ button to adjust the hour and press the MODE button to confirm. The minutes will flash, adjust by pressing the ▲12/24 button or ▼button
- The setting sequence is shown as follows: Hour, Minutes, Seconds, Year, Month/Date sequence, Month, Date

Note:

1. Seconds adjusted to zero only.
2. All setting modes will automatically exit in around 15 seconds without any adjustment.

Daily Alarm Setting:

- Press MODE button to set up the alarm. When in alarm mode, display shows "AL"
- When in Alarm mode, hold MODE button for 3 seconds to enter Alarm Time setting. Press ▲12/24 or ▼button to adjust the alarm time
- Press the MODE button to confirm the setting
- To activate the alarm slide the ALARM ON/OFF switch to ON position

Snooze Alarm Function:

- Slide the ALARM ON/OFF switch to ON to activate the alarm function. 📞 appears on the display
- The alarm will activate at the preset time and sound for 2 minutes then will stop automatically
- When the alarm activates you may:
 - Press the SNOOZE button and the alarm will stop and sound again after approximately 5 minutes, then it alerts again. The "Zz" flashes on the display during the snooze time; or
 - Press any button to stop the alarm or slide ALARM

ON/OFF switch to OFF to stop snooze alarm

12/24 Hour Display mode:

- Press ▲12/24 button to select 12 or 24 hours mode

THERMOMETER

- Press °C/°F button to select Temperature in Celsius or Fahrenheit
- If the temperature is out of the measureable range, LL.L (beyond the minimum temperature) or HH.H (beyond the maximum temperature) will be shown on the display

BACKLIGHT

- Press SNOOZE/LIGHT button to light the display for a few seconds

PRECAUTIONS

- Use a pin to press the reset button if the unit does not work properly
- The clock loses its time information when the

battery is removed

- Do not expose it to direct sunlight, heat, cold, high humidity or wet areas
- Never clean the clock using abrasive or corrosive materials or products. Abrasive cleaning agents may scratch plastic parts and corrode electronic circuits

CHANGING THE BATTERIES

- Do not mix new and used batteries, different types or brands together
- Only use AAA (1.5V) alkaline batteries in this clock
- Please dispose of used batteries in a responsible manner

THE SOURCE - WARRANTY



The Source warrants that this product will be free from defects in materials and workmanship for a period of one (1) year from the date of purchase. Within this period, simply take the product and your proof of purchase to any The Source store or participating dealer and the product will be replaced (where available) without charge. Any product which has been subject to misuse or accidental damage is excluded from this warranty. This warranty is only applicable to a product purchased through The Source company-owned stores or participating dealers in Canada where the warranty is included with the product. While this warranty does not confer any legal rights other than those set out above, you may have additional statutory rights which will vary under the laws of the various countries, states, provinces and other governmental entities in which The Source operates. This warranty is subject to all statutory rights you may have in Canada.

Imported by:
The Source,
Barrie, Ontario, Canada, L4M 4W5

Manufactured in China

www.thesource.ca



Please Recycle

© 2017 The Source
All rights reserved.